

NPS ARCHIVE
1966
ZAIMA, Y.

A PHASE LOCK SYSTEM FOR A SIGNAL
MODULATED BY A PN SEQUENCE

YUKIO ZAIMA

Library
J. S. Naval Postgraduate School
Monterey, California

DUDLEY KNOX LIBRARY
NAVAL POSTGRADUATE SCHOOL
MONTEREY, CA 93943-5101

A PHASE LOCK SYSTEM
FOR A SIGNAL MODULATED BY A PN SEQUENCE

by

Yukio Zaima
Lieutenant Commander, Japanese Maritime Self-Defense Force
B.S., U.S. Naval Postgraduate School, Monterey, 1965

Submitted in partial fulfillment
for the degree of
MASTER OF SCIENCE IN ELECTRONICS ENGINEERING
from the
UNITED STATES NAVAL POSTGRADUATE SCHOOL
May 1966

ABSTRACT

The dynamics of phase locked loops have been studied by many investigators for the cases of either a pure sinusoidal signal or for a pseudo noise (PN) sequence. This dissertation presents an analysis of a phase locked system consisting of a sinusoidal carrier modulated with a PN sequence. The effect of the modulation index of the phase shift modulation and the design of a loop filter for coherent detection of a PN sequence are analysed. Additionally, the error probability for each digit, when a likelihood detector is used in front of the delay lock discriminator for a PN sequence, is also converted to the delay error of the phase lock loop.

TABLE OF CONTENTS

Chapter	Title	Page
I.	Introduction	9
II.	Maximum-length Linear Shift Register Sequences	14
III.	Phase Locked Loop for Carrier	18
1.	Coherent Demodulator	18
2.	Noise in the Demodulator Output	21
IV.	Delay Lock Discriminator for a Binary Sequence	27
1.	Tracking and Acquisition Performance of a Delay-lock Discriminator	27
2.	Noise and its Effect on the Tracking	33
3.	The Effect of Input Limiting	40
V.	Threshold for This System	45
1.	Summary of the System Performance	45
2.	An Example of the Calculation Procedure	46
VI.	Conclusion	54
VII.	Acknowledgement	55
	Bibliography	56
Appendix I	Self Noise	57
Appendix II	Computer Program for Equation (4-18)	60
Appendix III	Subroutine "INTEG 1"	62

LIST OF ILLUSTRATIONS

Figure		Page
1-1	A Correlation Type Detector	9
1-2	Phase Locked Loop for Sinusoid	10
1-3	Delay Lock Discriminator for Binary Signal	11
1-4	A Phase Lock System for a Signal Modulated by a PN Sequence	12
2-1	n Stage Linear Shift Register	15
2-2	Autocorrelation Function of m-sequence	16
2-3	Power Spectral Density $G_A(\omega)$ of m-sequence	17
3-1	Phase Lock Loop for Coherent Demodulator	19
3-2	Phase Lock Loop	19
3-3	Vector Diagram for Phase Noise	19
3-4	Linearized Phase Lock Loop	20
3-5	Linearized Phase Lock Loop	20
4-1	Delay Lock Discriminator	27
4-2	Simplified Delay Lock Discriminator	29
4-3	Regions in Phase Trajectory	31
4-4	Phase Trajectory in Region B	32
4-5	Phase Trajectory in Region D	33
4-6	Phase Trajectory for $g = \infty$	34
4-7	Position Error x vs. Normalized Time τ for $g = \infty$	35
4-8	Velocity Error $\dot{x}$ vs. Normalized Time τ for $g = \infty$	36
4-9	Phase Trajectory for $g=10$	37
4-10	Position Error x vs. Normalized Time τ for $g=10$	38
4-11	Velocity Error $\dot{x}$ vs. Normalized Time τ for $g=10$	39
5-1	σ_θ^2 vs. θ for various K	49

5-2	A_0^2/A^2 vs. θ for various K	50
5-3	Optimum θ vs. K	51
5-4	Maximum A_0^2/A^2 vs. K	51
5-5	Delay Error σ_n^2/d^2 vs. K for various ω_0	52
5-6	ω_0 and Acquisition Time t_{lock} vs. K	53

TABLE OF SYMBOLS

$s(t)$ = an m-sequence with the number of digits $M=2^n - 1$ in a period,
and the duration of a digit d , amplitude ± 1

θ = the modulation index of the phase shift modulation

ω_c = the angular frequency of the carrier

A = amplitude of the incoming signal

$\sqrt{2}A\cos(\omega_c t + \theta s(t))$ = incoming signal

A_0 = expected value of the signal amplitude at the demodulator
output

$G_s(\omega)$ = the power spectral density of $s(t)$

$n(t)$ = band limited white Gaussian noise

$n_c(t)$ = an in-phase component of $n(t)$ with respect to the carrier

$n_s(t)$ = a quadrature component of $n(t)$ with respect to the carrier

$N(\omega)$ = the Fourier transform of $n(t)$

γ = one sided power spectral density of white Gaussian noise
(watts/cycle/second)

$F_1(\omega)$ = the loop filter of the demodulator

$F_2(\omega)$ = the loop filter of the delay lock discriminator

B_0 = band-width parameter of $F_1(\omega)$, (radian/sec)

ω_0 = band-width parameter of $F_2(\omega)$, (radian/sec)

$R_s(\tau)$ = autocorrelation function of $s(t)$

$R_{sn}(\tau)$ = crosscorrelation function of $s(t)$ and $n(t)$

$E[x]$ = the expected value of x

σ_n^2 = the variance of $n(t)$

CHAPTER I

INTRODUCTION

A correlation type detector or a matched filter is known to be optimum for detecting a signal in additive noise under a wide variety of conditions. The noise power is proportional to the effective bandwidth for the case of white Gaussian noise. We can improve the S/N ratio by narrowing the effective bandwidth if it does not restrict the information contained in the signal.




Fig. 1-1 A Correlation Type Detector

Consider the detector in Fig. 1-1. $s(t)$ is the incoming signal and $n(t)$ is additive white Gaussian noise. If we know the signal except for its phase, that is, the phase of the signal is the only information contained in the signal, we can generate $s(t + \tau)$ to multiply with the incoming signal. The low pass filter works like an averager in some sense as described later in section 4-3, and

$$y(t, \tau) = \frac{1}{T} \int_{t-\tau}^{t_1} s(t)s(t+\tau)dt + \frac{1}{T} \int_{t-\tau}^{t_1} n(t)s(t+\tau)dt.$$

If $s(t)$ and $n(t)$ are assumed to be stationary, $y(t, \tau)$ becomes a function of only τ for long T , and $y(t)$ becomes approximately the sum of the autocorrelation function of $s(t)$ " $R_s(\tau)$ " and the crosscorrelation function of $s(t)$ and $n(t)$ " $R_{sn}(\tau)$ ".

$$y(\tau) \doteq R_s(\tau) + R_{sn}(\tau)$$

If we can find a signal such that its autocorrelation function has a distinguished difference between the values of $\tau=0$ and $\tau \neq 0$, we will be able to utilize it for phase detection.

A sine function $\sqrt{2} A \cos \omega_c t$ has the autocorrelation function of $R_{\gamma}(\tau) = A^2 \cos \omega_c \tau$, and the phase locked loop for a sinusoidal function, like that shown in Fig. 1-2, has been studied by many investigators. Among them, R. Jaffe and E. Rechtin showed an optimum filter design for a linearly approximated loop [5], A. J. Viterbi showed the transient response for θ_1 having a second order polynomial in the nonlinear system, [10] W. F. Roland defined the threshold criterion by the minimum of the cycles of slip and showed its utility through experimental results in his thesis for the degree of M. S. [7]




Fig. 1-2 Phase Locked Loop for Sinusoid

The binary signal has only two possibilities for each digit, ONE or ZERO, or -1 or +1, but sequences of binary digits show many interesting and complex characteristics. Some sequences represent codes for which maximum likelihood detection is possible. They are classified by the crosscorrelation function in each code set; orthogonal, biorthogonal and simplex. [2]

There are also some special group of binary sequences especially adapted for phase detection; the PN sequence, especially the maximum-length linear shift register sequence (m-sequence), will be explained a little more precisely in Chapter 2. R. H. Barker defined "Group Synchronization" so as to pin-point effectively the origin in time for a binary sequence, and showed a matched filter, and also the characteristics and some patterns of this sequence. [1]

The complementary binary sequences studied by S. Jauregui, Jr. used

the same kind of matched filters and when used in a differential pair these eliminate small ambiguities in the output. [6] Both sequences can be used in the form of discrete pulse sequences.

PN sequences are adequate for the use of both continuously and periodically incoming signals. J. J. Spilker proposed a delay lock discriminator shown in Fig. 1-3, using the combination of two autocorrelation functions having two digit interval difference γ . [8] J. C. Springett showed a combination of clock and PN sequence to produce a controlling voltage proportional to the phase difference. [9] M. F. Easterling introduced a tracking system using a combination of clock and several codes and produced synchronization, code by code, separately. [3] In this system,




Fig. 1-3 Delay Lock Discriminator for Binary Signal

only the clock has a phase locked loop. The synchronization of the other codes is evaluated by a correlation indicator. For the system which needs long distance tracking and does not require quick reaction for the variation of the targets dynamics, this will be all right, but if we need automatic synchronization and very rapid acquisition, this will not be adequate.

Since the second one has many weak ambiguous points between distinguished phase lock points, we prefer Spilker's delay lock discriminator rather than Springett's.

The periodic sequence is preferable for phase lock loops to the non-periodic because of the possibility of continuous control.

This paper treats the phase lock system for a carrier phase shift

modulated by a PN sequence, as shown in Fig. 1-4. $s(t)$ is a maximum-length linear shift register sequence with the number of digits in a period $M=2^n-1$, and the duration of a digit d . $n(t)$ is white Gaussian noise and has the following narrow band approximation

$$n(t) = n_i(t)\cos\omega_c t + n_q(t)\sin\omega_c t$$




Fig. 1-4 A Phase Lock System for a Signal Modulated by a PN Sequence

Many papers have analyzed each separate stage presented so far, but not the combined system. There are two problems to be solved for this system; what is the effect of θ on the phase lock performance of this system, and if $F_1(\omega)$ and $F_2(\omega)$ have the same type of low pass filter as that derived by Jaffe and Rechtin, how can we determine adequate bandwidths for these filters? θ determines the ratio of the I component and Q component of incoming signals, and also the necessary bandwidth for the input of this system. If θ is large, the output modulating signal will be large, but due to the large phase error of the demodulating stage, the effective amplitude will decrease. The loop bandwidth of each stage is related to the transient response for tracking and the required reduction in the noise output.

This report will summarize those relations determined by other authors for each stage, and will further derive the threshold S/N ratio and the performance of this system. Chapter 2 considers the characteristics of m-sequences. Chapter 3 shows the demodulation of an incoming modulated

carrier and the output of this stage.

The delay lock discriminator for an m-sequence will be analyzed in Chapter 4 with the effect of a limiter in front of this stage included in the performance.

Chapter 5 summarises the system results and illustrates by an example the conclusion of the next chapter. This illustration will not show any particularly interesting value for θ or other parameters. It is simply an example of the evaluation of system parameters and of design decision, but it is hoped that this will give a rough idea of the overall performance of such systems and will give some understanding of the role played by each parameter in the design of a system employing PN modulation of a sinusoidal carrier.

CHAPTER II

MAXIMUM-LENGTH LINEAR SHIFT REGISTER SEQUENCE

The autocorrelation function of a binary sequence of length M ,

$s(i) = \{a_1, a_2, \dots, a_M\}$, where $a_i = \pm 1$, is defined as

$$\rho_s(j) = \frac{1}{M} \sum_{i=1}^M a_i a_{i+j} \quad i+j : \text{modulo } M$$

If $\rho_s(0) = 1$

$$\rho_s(j) = a \neq 1 \quad (1 \leq j < M)$$

then $s(i)$ is called a two-level sequence, and if, moreover, $\rho_s(j) = -\frac{1}{M}$ for $j \neq 0$ (modulo M), the sequence is sometimes called a pseudo-noise (PN) sequence. Exactly, a PN sequence has to have the following three "randomness properties". [4]

R-1 (the balance property) In each period of the sequence the number of ONE's differs from the number of ZERO's by at most 1.

R-2 (the run property) Among the runs of ONE's and of ZERO's in each period, one-half the runs of each kind are of length one, one fourth of each kind are of length two, one eighth are of length three, and so on as these fractions give meaningful numbers of runs.

R-3 (the correlation property) If a period of the sequence is compared, term by term, with any cyclic shift of itself, the number of agreements differs from the number of disagreements by at most 1.

There are four types of PN sequences, corresponding to the length M . [2]

- | | |
|---|--|
| 1) $M = 2^n - 1$ | (m-sequences) |
| 2) $M = 4t - 1$ is prime | (quadratic residue or Legendre sequence) |
| 3) $M = 4t - 1 = 4x^2 + 27$ is prime | (Hall sequence) |
| 4) $M = p(p+2)$ where both $p, p+2$ are prime | (twin prime sequence) |

Among them the maximum-length linear shift register sequence (m-sequence) has the delay-and-add property and is generated by a linear shift register. This is also convenient to generate in the phase lock loop, therefore in this report the m-sequence is used as a PN sequence.




Fig. 2-1 n Stage Linear Shift Register

In the n stage linear shift register shown in Fig. 2-1, the output sequence is always periodic with a period $p \leq M = 2^n - 1$, and when period is M, that sequence is called a maximum-length linear shift register sequence. This m-sequence has the delay-and-add property, that is, if the sequence is added term-by-term modulo 2 to a cyclic shift of itself, the resulting sequence is another cyclic shift of the original sequence. This property is possessed only by the binary sequence $\{a_1, a_2, \dots, a_M\}$ ($a_i = 1$ or 0) which satisfies a linear recursion relation

$$a_k = \sum_{i=1}^n c_i a_{k-i}$$

for all k

$k-i : (\text{modulo } M)$

$c_i = 1$ or 0

summation is modulo 2

and $M = 2^n - 1$. [2]

m-sequence satisfies this.

Consider an m-sequence $s(i) = \{a_1, a_2, \dots, a_M\}$. The autocorrelation function of this sequence $\rho_s(k)$ is

$$\rho_s(k) = \frac{1}{M} \sum_{i=1}^M a_i \oplus a_{i+k}$$

$\oplus$, sum of modulo 2

Using the delay-and-add property,

$$\begin{aligned} \rho_s(k) &= \frac{1}{M} \sum_{i=1}^M a_{i+j} = \frac{1}{M} \{ (\# \text{ of ONE's}) \times (-1) + (\# \text{ of ZERO's}) \times (1) \} \\ &= \frac{1}{M} \left\{ \frac{M+1}{2} \times (-1) + \frac{M-1}{2} \times (+1) \right\} \\ &= -\frac{1}{M} \quad \text{for } k \neq 0 \text{ (modulo } M) \end{aligned}$$

$$\rho_s(0) = \frac{1}{M} \sum_{i=1}^M a_i \oplus a_i = \frac{1}{M} \sum_{i=1}^M 1 = 1$$

(If we replace ONE and ZERO with -1 and +1, we can use multiple instead of $\oplus$). For the wave form $s(t)$ which takes the value of +1 or -1 according to $s(i)$ at time $(i-1)d \leq t < id$, the autocorrelation function $\rho_s(\tau)$ is,

$$\rho_s(\tau) = \frac{1}{T} \int_0^T s(t) s(t+\tau) dt \quad T = Md$$

For $\tau = 0$ or kd (k : integer)

$$\begin{aligned} \rho_s(0) &= \frac{1}{Md} \int_0^{Md} \{s(t)\}^2 dt = 1 \\ \rho_s(kd) &= \frac{1}{Md} \int_0^{Md} s(t) s(t+kd) dt = \frac{1}{Md} \int_0^d dt \sum_{i=1}^M a_i a_{i+k} = -\frac{1}{M} \end{aligned}$$

If $\tau = kd + \delta$ and $0 < \delta < d$, then first $(d-\delta)$ of each digit of $s(t)$

corresponds with the last part $(d-\delta)$ of $s(t+kd)$, and the remaining δ of $s(t)$ corresponds with the first part δ of $s(t+(k+1)d)$.

$$\begin{aligned} \rho_s(\delta) &= \frac{1}{Md} \left\{ \int_0^{d-\delta} dt \sum_{i=1}^M a_i^2 + \int_{d-\delta}^d dt \sum_{i=1}^M a_i a_{i+1} \right\} \\ &= 1 - \frac{\delta}{d} - \frac{\delta}{M} \\ \rho_s(kd + \delta) &= \frac{1}{Md} \left\{ \int_0^{d-\delta} dt \sum_{i=1}^M a_i a_{i+k} + \int_{d-\delta}^d dt \sum_{i=1}^M a_i a_{i+k+1} \right\} \\ &= -\frac{1}{M} \end{aligned}$$

$\rho_s(\tau)$ is an even function and we can get the same result for any negative value of τ , and the autocorrelation function of $s(t)$ has the shape shown in Fig. 2-2.




Fig. 2-2 Autocorrelation Function of m-sequence

The power spectral density of $s(t)$, $G_s(\omega)$ is derived by using the Wiener-Khinchine relation.

$$G_s(\omega) = \int_{-\infty}^{\infty} \rho_s(\tau) e^{-j\omega\tau} d\tau$$

$$= \frac{M+1}{M^2} \left(\frac{\sin(\omega d/2)}{\omega d/2} \right)^2 \sum_{\substack{n=-\infty \\ n \neq 0}}^{\infty} \delta\left(\omega - \frac{2\pi n}{Md}\right) + \frac{1}{M^2} \delta(\omega)$$




Fig. 2-3 Power Spectral Density $G_s(\omega)$ of m-sequence

When we consider the necessary bandwidth of the band pass filter for the modulated input $\sqrt{2}A\cos(\omega_c t + \theta s(t))$, where $0 < \theta < \frac{\pi}{2}$, we can analyze $s(t)$ into frequency components. If we pick up one frequency, then that frequency component will be

$$\sqrt{2} \frac{\sqrt{M+1}}{M} \frac{\sin \frac{\pi n}{M}}{\frac{\pi n}{M}} \sin\left(\frac{2\pi n}{Md} t + \phi_n\right)$$

Since M is a large number, $\frac{\sqrt{M+1}}{M} \doteq \frac{1}{\sqrt{M}} \ll 1$ and the amplitude of each frequency component is supposed to be very small. A phase modulated carrier ω_c by a modulating frequency ω_m , with small modulation index $\beta \ll 1$, is expressed as

$$\cos(\omega_c t + \beta \sin \omega_m t) \approx \cos \omega_c t - \beta \sin \omega_m t \sin \omega_c t$$

This has frequency components of ω_c , $\omega_c \pm \omega_m$. The frequency components of the signal $\sqrt{2}A\cos(\omega_c t + \theta s(t))$ are derived in the same way as for small modulation index $\beta \ll \frac{\pi}{2}$, therefore in order to preserve almost all power of this incoming signal we can pass only the frequency between $\omega_c \pm \frac{2\pi}{d}$, because almost all the power of $s(t)$ is included inside of $\pm \frac{2\pi}{d}$.

CHAPTER III

PHASE LOCKED LOOP FOR CARRIER

3.1 Coherent Demodulator

Since $s(t) = \pm 1$, we can separate the input signal $\sqrt{2}A\cos(\omega_c t + \theta s(t))$ into two parts.

$$\sqrt{2}A\cos(\omega_c t + \theta s(t)) = \sqrt{2}A\cos\theta \cos\omega_c t + s(t)\sqrt{2}A\sin\theta \sin\omega_c t$$

If we can lock the phase of the local oscillator to the carrier frequency, we can get the modulating signal $\sqrt{2}A\sin\theta s(t)$. While $\sqrt{2}A\cos\theta \cos\omega_c t$ can be used for that phase lock. Hence, there will be an optimum value of θ to get the maximum signal to noise ratio in the output.

Phase jitter in the local oscillator, caused by the output of $\sqrt{2}As(t)\sin\theta$, plus input noise causes the amplitude variation of signal output in the form of $\sqrt{2}As(t)\sin(\theta + \theta_0)$ and acts to increase the noise input for the next stage.

The crosscorrelation function of $\cos(\omega_c t + \theta s(t))$ and $\cos\omega_c t$ is

$$\begin{aligned} \rho(\tau) &= \frac{1}{2T} \int_{-T}^T \cos(\omega_c t + \theta s(t)) \cos\omega_c(t+\tau) dt \\ &= \frac{1}{2T} \int_{-T}^T \frac{1}{2} [\cos\theta \cos(2\omega_c t + \omega_c \tau) - s(t) \sin\theta \sin(2\omega_c t + \omega_c \tau) \cos\omega_c \tau \cos\theta \\ &\quad + s(t) \sin\theta \sin\omega_c \tau] dt \\ &= \frac{1}{2} \cos\theta \cos\omega_c \tau - \frac{1}{M} \sin\theta \sin\omega_c \tau \\ &\doteq \frac{1}{2} \cos\theta \cos(\omega_c \tau + \phi) \\ \phi &= \tan^{-1} \left(\frac{1}{M} \tan\theta \right) \end{aligned}$$

ϕ is negligible when M is large and $\tan\theta$ is not excessive and we can make a phase lock loop like Fig. 3-1.

As far as this phase-lock loop is concerned, the first low pass filter can be neglected and letting the low pass filter be denoted as




Fig. 3-1 Phase Lock Loop for Coherent Demodulation

$F_1(\omega)$, we can simplify this loop like Fig. 3-2.




Fig. 3-2 Phase Lock Loop

Noise input is assumed to be band limited white Gaussian noise, and using narrow band approximation

$$n(t) = n_i(t) \cos \omega_c t + n_q(t) \sin \omega_c t$$

where $n_i(t)$ and $n_q(t)$ are normally distributed time functions varying slowly compared with ω_c , and $\text{av.}(n_i) = \text{av.}(n_q) = 0$, the variances

$$\sigma_{n_i}^2 = \sigma_{n_q}^2 = N = \eta W$$

W bandwidth (cycles/sec)

η one sided power spectral density of white Gaussian noise (watts sec/cycle)

When we look at the vector of this input at the vicinity of the phase locked point in Fig. 3-3, $\sqrt{2}A \sin \theta$ and n_q are found as the causes of phase deviation, and since they are independent, their effects will be evaluated in the sum of variances.




Fig. 3-3 Vector Diagram for Phase Noise

By approximating

$$\sin(\lambda_i - \lambda_o) = \lambda_i - \lambda_o$$

$$\cos(\lambda_i - \lambda_o) = 1$$

in the vicinity of the phase locked point, we can linearize the loop as shown in Fig. 3-4. The output of the voltage controlled oscillator is the derivative of λ_o and proportional to the input level. Thus we can also modify them in Fig. 3-4.




Fig. 3-4 Linearized Phase Lock Loop




Fig. 3-5 Linearized Phase Lock Loop

Let $k_m C g_v = K$


$$A \cos \theta = A_1$$

then we can get the loop of Fig. 3-5. If we neglect the effect of $\theta \Delta(\omega)$, the solution for optimum performance is shown in the paper of R. Jaffe and E. Rechtin. [5]

Using that result, $F_1(\omega)$ is defined as $F_1(\omega) = \frac{B_o^2 + \sqrt{2} B_o j\omega}{A_1 K j\omega}$ and the closed transfer function $H(\omega)$ is

$$H(\omega) = \frac{A_1 K F_1(\omega) / j\omega}{1 + A_1 K F_1(\omega) / j\omega} = \frac{B_o^2 + \sqrt{2} B_o j\omega}{B_o^2 + \sqrt{2} B_o j\omega + (j\omega)^2}$$

The network for $F_1(\omega)$ is approximately constructed by RC components.



$$C = \frac{\sqrt{2}}{B_0 R_2}$$

$$R_1 = R_2 \left(\frac{A_0 K}{\sqrt{2} B_0} - 1 \right) \gg R_2$$

From the linearized transfer function $H(\omega)$, we can also derive the error

$$\begin{aligned} \mathcal{E}(\omega) &= \Lambda_i(\omega) - \Lambda_o(\omega) \\ &= \Lambda_i(\omega) \{1 - H(\omega)\} \\ &= \Lambda_i(\omega) \frac{-\omega^2}{B_0^2 + \sqrt{2} B_0 j \omega - \omega^2} \end{aligned} \quad (3-1)$$

For the input of frequency deviation $\Delta\omega$

$$\begin{aligned} \Lambda_i(\omega) &= \frac{\Delta\omega}{-j\omega^2} \\ \mathcal{E}(\omega) &= \frac{\Delta\omega}{B_0^2 + \sqrt{2} B_0 j \omega - \omega^2} \end{aligned} \quad (3-2)$$

$$\begin{aligned} \mathcal{E}(t) &= \frac{1}{2\pi} \int_{-\infty}^{\infty} \mathcal{E}(\omega) e^{j\omega t} d\omega = \frac{\sqrt{2}\Delta\omega}{B_0} e^{-\frac{B_0}{\sqrt{2}}t} \sin \frac{B_0}{\sqrt{2}}t \quad t > 0 \\ &= 0 \quad t < 0 \end{aligned} \quad (3-3)$$

$$E_r^2 = \int_0^{\infty} \mathcal{E}(t)^2 dt = \frac{(\Delta\omega)^2}{2\sqrt{2} B_0^3} \quad (3-4)$$

Max $\mathcal{E}(t)$ is derived by putting $\frac{d\mathcal{E}}{dt} = 0$.

$$t|_{\max \mathcal{E}} = \frac{\pi}{2\sqrt{2} B_0} \quad (3-5)$$

$$\mathcal{E}(t)|_{\max} = \frac{\Delta\omega}{2.19 B_0} \quad (3-6)$$

The effective bandwidth of $H(\omega)$ is

$$\begin{aligned} \frac{1}{2\pi} \int_{-\infty}^{\infty} |H(\omega)|^2 d\omega &= \frac{1}{2\pi} \int_{-\infty}^{\infty} \frac{1 + 2(\omega/B_0)^2}{1 + (\omega/B_0)^4} d\omega \\ &= \frac{3\sqrt{2}}{4} B_0 = 1.06 B_0 \quad (\text{cycles/sec}) \end{aligned} \quad (3-7)$$

The phase error due to input noise is normal with zero mean and the variance is

$$\begin{aligned} \sigma_{\theta_n}^2 &= \frac{1}{2\pi} \int_{-\infty}^{\infty} \left| \frac{N_B(\omega)}{\sqrt{2} A_1} \right|^2 |H(\omega)|^2 d\omega \\ &= \frac{7}{2 A^2 \cos^2 \theta} \frac{3\sqrt{2}}{4} B_0 = \frac{37 B_0}{4\sqrt{2} A^2 \cos^2 \theta} \end{aligned} \quad (3-8)$$

3.2 Noise In the Demodulator Output

As shown in the previous section, the output near the phase locked point is

$$A \cos \theta \sin \theta_0 + A s(t) \sin \theta \cos \theta_0 + n_f(t) \quad (3-9)$$

$$\text{var}(n_f(t)) = \gamma \frac{1}{\alpha}$$

If we subtract the required signal $As(t)\sin\theta$, then the remaining is unnecessary and is considered as noise, which is

$$A\cos\theta\sin\theta_0 + As(t)\sin\theta(1-\cos\theta_0) + n_f(t)$$

a) The distribution of θ_0 .

The phase error θ_0 in eq.(3-9) is the sum of the contribution from the noise input and the self noise of $s(t)$.

Since $H(\omega)$ is assumed to work in the linear region and n_f is normal, the phase error produced by the noise input θ_n is approximately distributed normally.

The distribution of phase error by the self noise θ_s is derived as follows.

Consider a randomness property of an m-sequence, "R-2" (the Run Property), "Among the runs of ONE's and of ZERO's in each period, the number of runs of length i is $1/2^i$ of the runs of each kind, and $n = \log_2(M+1)$ is the maximum length". When we compare these distributions, we can see each digit has the probability of $\frac{1}{2}$ to be +1 and $\frac{1}{2}$ to be -1. If we take a large number of digits m , then the probability it contains k of +1 is binomial distribution.

$$P(k \text{ of } +1 \text{ out of } m \text{ digits}) = \binom{m}{k} \left(\frac{1}{2}\right)^m$$

Therefore if we take m digits and count the difference of the number of -1 from the number of +1, the probability of the difference to be i is

$$P(\text{difference} = i) = \binom{m}{\frac{m+i}{2}} \left(\frac{1}{2}\right)^m$$

(m and i should be both even, or odd, but since m is large, for a small number of i , we can adjust m as m or $m+1$ according to the number of i for approximation). For a large number of m , we can approximate it with normal distribution.

Since a low pass filter is, in some sense, an averager, we can

conclude that θ_0 is also approximately normally distributed with zero mean and with variance equal to $\theta_0^2 B_0 d$. (See Appendix I).

θ_n and θ_0 have different kinds of input and they are independent, therefore, the probability distribution function of $\theta_0 = \theta_n + \theta_0$ is also normal with zero mean and variance $\sigma_{\theta_0}^2 = \sigma_{\theta_n}^2 + \sigma_{\theta_0}^2$.

b) The probability distribution of $\sin \theta_0$, and $(1 - \cos \theta_0)$ where θ_0 has a normal distribution function.

Considering the noise output by θ_0 , if we want to get good performance in the next stage, θ_0 should be desired to be a very small value in the variance, if not, this system would not work satisfactorily. If θ_0 has a small variance, the contribution of θ_0 to $A \cos \theta \sin \theta_0$ is approximately evaluated mainly by θ_0 neglecting the other terms of series expansion of $\sin \theta_0$, and for $(1 - \cos \theta_0)$ by $\theta_0^2/2$.

$$A \cos \theta \sin \theta_0 \doteq A \theta_0 \cos \theta$$

$$A s(t) \sin \theta (1 - \cos \theta_0) \doteq \frac{\theta_0^2}{2} A s(t) \sin \theta$$

The first one has normal distribution and the second one $\frac{\theta_0^2}{\sigma_{\theta_0}^2}$ is Chi-square distribution with degree of freedom 1.

Looking at θ_0 which is the output of $H(\omega)$, we can see that it varies very slowly compared with each digit interval d , but since the ratio of maximum frequency deviation of the input to ω_c is the same as the ratio of the deviation of digit duration to d , and the filter parameter B_0 is wider than the filter parameter ω_0 in the next stage, θ_0 varies more rapidly than the fluctuation of phase in the next stage. Therefore the effect of θ_0 to the next stage is considered as if $A \cos \theta \sin \theta_0$ were added to n_f as random Gaussian noise in the approximation of $(A \cos \theta) \theta_0$, and since $A \sin \theta (1 - \cos \theta_0)$ is approximated by χ^2 , at the output of the next stage they have the same effect as the decrease of amplitude by a factor like an average of many digits.

The averaged power of $A_s(t)\sin\theta\cos\theta_0$ is

$$\begin{aligned}
 & A^2 \sin^2 \theta \int_{-\infty}^{\infty} \cos^2 \theta_0 \frac{1}{\sqrt{2\pi} \sigma_{\theta_0}} e^{-\theta_0^2 / 2\sigma_{\theta_0}^2} d\theta_0 \\
 &= \frac{A^2 \sin^2 \theta}{2} \left[\int_{-\infty}^{\infty} \frac{1}{\sqrt{2\pi} \sigma_{\theta_0}} e^{-\theta_0^2 / 2\sigma_{\theta_0}^2} d\theta_0 + \int_{-\infty}^{\infty} \frac{1}{\sqrt{2\pi} \sigma_{\theta_0}} \cos 2\theta_0 e^{-\theta_0^2 / 2\sigma_{\theta_0}^2} d\theta_0 \right] \\
 &= \frac{A^2 \sin^2 \theta}{2} \left[1 + \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} \cos 2\sigma_{\theta_0} x e^{-x^2 / 2} dx \right] \\
 &= A^2 \sin^2 \theta \left[\frac{1}{2} + \frac{1}{2} e^{-\sigma_{\theta_0}^2 / 2} \right] \quad (3-13)
 \end{aligned}$$

or $(1 - \cos \theta_0) A \sin \theta \doteq \frac{\sigma_{\theta_0}^2}{2} A \sin \theta$
 $\left(\frac{\theta_0}{\sigma_{\theta_0}}\right)^2$ is distributed in χ_1^2 distribution, and if we take sum of n digits, it becomes χ_n^2

$$E\left(\frac{\chi_n^2}{n}\right) = 1, \text{ var.}\left(\frac{\chi_n^2}{n}\right) = 2/n$$

And as n becomes large, the distribution of the average becomes very close to 1.

$$\text{av.}(A \sin \theta \cos \theta_0) \doteq \left(1 - \frac{\sigma_{\theta_0}^2}{2}\right) A \sin \theta \quad (3-14)$$

Comparing this with $\sqrt{\frac{1}{2} + \frac{1}{2} e^{-\sigma_{\theta_0}^2 / 2}}$, for small values of $\sigma_{\theta_0}^2$,

$$\sqrt{\frac{1}{2}(1 + e^{-\sigma_{\theta_0}^2 / 2})} \doteq \sqrt{1 - \frac{\sigma_{\theta_0}^2}{4}} = 1 - \frac{\sigma_{\theta_0}^2}{2}$$

The result shows good agreement with eq.(3-14).

c) Correlation of θ_0 and $n_f(t)$

From the argument so far, we could derive the approximate output of the discriminator, and it is shown as follows.

$$\begin{aligned}
 & \sqrt{\frac{1}{2}(1 + e^{-\sigma_{\theta_0}^2 / 2})} (A \sin \theta) s(t) && \text{as the signal} \\
 & + (A \cos \theta) \theta_0 + n_f(t) && \text{as noise} \quad (3-15)
 \end{aligned}$$

What is the distribution of noise as a whole?

$$\theta_0 = \theta_n + \theta_d$$

θ_d is uncorrelated with θ_n and so with $n_f(t)$.

Therefore the correlation of θ_0 and $n_f(t)$ is the correlation of θ_n and $n_f(t)$.

In a linear system of transfer function $H(\omega)$,

$$\theta_n = \frac{N_f(\omega)}{\sqrt{2} A \cos \theta} H(\omega)$$

$$h(t) = \sqrt{2} B_0 e^{-\frac{B_0}{2} t} \cos \frac{B_0}{2} t \quad \text{for } t > 0 \quad (h(t) = 0 \text{ for } t < 0)$$

$$\theta_n(t) = \int_0^\infty n(t-\tau)h(\tau)d\tau$$

Correlation of θ_n and $n_g(t)$ is

$$\begin{aligned} r_{\theta n}(\lambda) &= \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^T n(t+\lambda) \theta_n(t) dt \\ &= \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^T n(t+\lambda) \int_0^\infty n(t-\tau)h(\tau)d\tau dt \\ &= \lim_{T \rightarrow \infty} \frac{1}{2T} \int_0^\infty h(\tau) \int_{-T}^T n(t+\lambda)n(t-\tau)dtd\tau \\ &= \int_0^\infty h(\tau) \lim_{T \rightarrow \infty} \frac{1}{2T} \int_{-T}^T n(t+\lambda)n(t-\tau)dtd\tau \\ &= \int_0^\infty h(\tau) R_n(\lambda-\tau) d\tau = \int_0^\infty h(\tau) \gamma \delta(\lambda-\tau) d\tau \\ &= \frac{B_0 \gamma}{A \cos \theta} e^{-\frac{B_0}{\sqrt{2}} \lambda} \cos \frac{B_0}{\sqrt{2}} \lambda \end{aligned} \quad (3-16)$$

for $\lambda = 0$

$$r_{\theta n}(0) = \frac{B_0 \gamma}{A \cos \theta} \quad (3-17)$$

The variances of θ_0 and $n_g(t)$ are

$$\begin{aligned} \sigma_{\theta_0}^2 &= \frac{3 \gamma B_0}{4 \sqrt{2} A^2 \cos^2 \theta} + \theta^2 B_0 d \\ \sigma_{n_g}^2 &= \gamma \frac{1}{d} \end{aligned} \quad (3-18)$$

The normalized correlation coefficient ρ is

$$\rho = \frac{r_{\theta n}(0)}{\sigma_{\theta_0} \sigma_{n_g}} \quad (3-19)$$

Letting $\theta_0 A \cos \theta = x$

$$n_g(t) = y$$

$$E(x) = E(y) = 0$$

$$\sigma_x^2 = A^2 \cos^2 \theta \sigma_{\theta_0}^2$$

$$\sigma_y^2 = \sigma_{n_g}^2$$

$$p(x, y) = \frac{1}{2\pi \sigma_x \sigma_y \sqrt{1-\rho^2}} \exp \left[\frac{-1}{2(1-\rho^2)} \left(\frac{x^2}{\sigma_x^2} - \frac{2\rho xy}{\sigma_x \sigma_y} + \frac{y^2}{\sigma_y^2} \right) \right]$$

Changing variables

$$x+y=u$$

$$y=v$$

$$\begin{aligned} p(u) &= \int_{-\infty}^{\infty} \frac{1}{2\pi \sigma_x \sigma_y \sqrt{1-\rho^2}} \exp \left[\frac{(u-v)^2}{2(1-\rho^2)} \left(\frac{1}{\sigma_x^2} - \frac{2\rho(u-v)v}{\sigma_x \sigma_y} + \frac{v^2}{\sigma_y^2} \right) \right] dv \\ &= \exp \left[-\frac{u^2}{2(\sigma_x^2 + 2\rho \sigma_x \sigma_y + \sigma_y^2)} \right] \int_{-\infty}^{\infty} \frac{1}{2\pi \sqrt{1-\rho^2} \sqrt{\sigma_x^2 + 2\rho \sigma_x \sigma_y + \sigma_y^2}} e^{-\frac{z^2}{2(1-\rho^2)}} dz \end{aligned}$$

$$\text{where } z = \sqrt{\frac{1}{\sigma_x^2} + \frac{2\rho}{\sigma_x \sigma_y} + \frac{1}{\sigma_y^2}} v + \frac{u}{\sigma_x} \sqrt{\frac{(\sigma_x + \rho \sigma_y)}{\frac{1}{\sigma_x^2} + \frac{2\rho}{\sigma_x \sigma_y} + \frac{1}{\sigma_y^2}}}$$

$$p(u) = \frac{1}{\sqrt{2\pi} \sqrt{\sigma_x^2 + 2\rho \sigma_x \sigma_y + \sigma_y^2}} \exp \left[-\frac{u^2}{2(\sigma_x^2 + 2\rho \sigma_x \sigma_y + \sigma_y^2)} \right]$$

$$\sigma_n^2 = \sigma_x^2 + 2\rho\sigma_x\sigma_y + \sigma_y^2$$

$$u = n_o(t)$$

The output is now simplified as

$$\sqrt{\frac{1}{2}(1 + e^{-\sigma_{\theta_0}^2/2})} (A \sin \theta) s(t) + n_o(t)$$

$n_o(t)$ is normal with zero mean and variance σ_n^2 .

The power spectral density of this noise is not flat in the bandwidth of $1/d$, because θ_0 has the approximate bandwidth of B_0 . Let the power spectral density of $n_o(t)$ be $G_n(\omega)$

$$\sigma_n^2 = \frac{1}{2\pi} \int_{-\infty}^{\infty} G_n(\omega) d\omega$$

If we divide this by $G_n(\omega)|_{\omega=0}$, then we can get the effective bandwidth B_e . The low pass filter used in the next stage has narrower bandwidth than B_0 , then we can use $(\frac{\sigma_n^2}{B_e})$ as the approximation of $G_n(\omega)$ because the value of $G_n(\omega)$ inside of that bandwidth ω_0 mainly contributes to the output.

Let the Fourier transform of $n_f(t)$ be $N_f(\omega)$, then the Fourier transform of $(A \cos \theta) \theta_0$ is $\frac{N_f(\omega)}{\sqrt{2}} H(\omega) + (A \cos \theta) \Theta_0(\omega)$

$$\frac{N_f(\omega)}{\sqrt{2}} H(\omega) \Big|_{\omega=0} = \frac{N_f(0)}{\sqrt{2}}$$

$$(A \cos \theta) \Theta_0(\omega) \Big|_{\omega=0} = (A \cos \theta) \frac{1}{M} \neq 0$$

$$G_n(\omega) \Big|_{\omega=0} = \left\{ \left| N_f(\omega) + \frac{N_f(\omega)}{\sqrt{2}} H(\omega) \right|^2 \right\} \Big|_{\omega=0} \doteq 2.91 \eta$$

CHAPTER IV

DELAY LOCK DISCRIMINATOR FOR A BINARY SEQUENCE

4.1 Tracking and Acquisition Performance of a Delay-lock Discriminator

This has been solved by J. J. Spilker, [8] and here we would like to follow the general results. This section explains the tracking and acquisition performance, and the next section shows the effect of noise on the performance.

If we take the difference of the outputs from two crosscorrelators which differ two digit intervals in Fig. 4-1, and separate it into an averaged value $A_0 k D_d(\epsilon)$ and another fluctuating part (self-noise) $A_0 k n_d(t, \epsilon)$, these are derived as follows.





Fig. 4-1 Delay Lock Discriminator

The autocorrelation function of an m-sequence is already shown in Fig. 2-1, and from that figure we can draw $D_d(\epsilon)$ as this.



$$D_d(\epsilon) = E[s(t+T)s(t+d+\hat{T}) - s(t+T)s(t-d+\hat{T})] \\ = \{R_d(\epsilon-d) - R_d(\epsilon+d)\} \quad (4-1)$$

The self-noise in the output of the multiplier network is

$$n_d(t, \epsilon) = s(t+d+\hat{T})s(t+T) - s(t-d+\hat{T})s(t+T) - D_d(\epsilon) \quad (4-2)$$

For $\epsilon = kd$, k : integer, using the delay-and-add property,

a) $k=0$, (modulo M)

$$n_d(t, kd) = s(t+d+T)s(t+T) - s(t-d+T)s(t+T) \\ = s(t+T+d)s(t+T) - s(t+T-d)s(t+T-d) \\ = s(t+T+jd) - s(t+T-d+jd) \\ = s(t+T+jd) - s(t+T+(j-1)d) \quad (4-3)$$

b) $k=\pm 1$, (modulo M)

$$n_d(t, kd) = s(t+d+T+d)s(t+T) - s(t-d+T+d)s(t+T) - D_d(\pm d) \\ = \begin{cases} 1 - s(t+T+id) - \frac{M+1}{M} \\ s(t+T+id) - 1 + \frac{M+1}{M} \end{cases} \\ = \mp [s(t+T+id) - \frac{1}{M}] \quad (4-4)$$

c) $k=\text{other integer}$

$$n_d(t, kd) = s(t+T+rd) - s(t+T+qd) \quad (4-5)$$

Further discussions of this self-noise, i.e. its power spectral density and the output from the loop will be explained in the next section.

A) The output of the crosscorrelator network is

$$kA_o [D_d(\epsilon) + n_d(t, \epsilon) + n_o(t) / A_o]$$

This is filtered by a low pass filter $g_f F_2(\omega)$ and drives the voltage controlled clock generator. This relation is now shown in the following Fig. 4-2. Obviously the control part of the crosscorrelator output $D_d(\epsilon)$ is a function of $T - \hat{T} = \epsilon$, and T is the integral of the controlled frequency.

$$\hat{T} = \frac{d}{j\omega} kA_o g_c g_f F_2(\omega) [D_d(\epsilon) + n_d(\omega, \epsilon) + n_o(\omega) / A_o]$$




Fig. 4-2 Simplified Delay Lock Discriminator

In the locked-on state, $\epsilon < d$,

$$D_d(\epsilon) = \frac{M+1}{M} \frac{\epsilon}{d}$$

$$\epsilon = T - \hat{T}$$

$$j\omega \hat{T} = dkA_0 g_c g_f \frac{M+1}{M} F_z(\omega) \left[\frac{\epsilon}{d} + \frac{n_d + n_o/A_0}{(M+1)/M} \right] \quad (4-6)$$

Using the same kind of filter as used in Chapter 3,

$$F_z(\omega) = \frac{\omega_o^2 + \sqrt{2} \omega_o j \omega}{\omega_o^2 + g_o j \omega} \doteq \frac{\omega_o^2 + \sqrt{2} \omega_o j \omega}{g_o j \omega}$$

$$g_o = kA_0 g_c g_f$$

$$\frac{\hat{T}}{d} = \frac{(\omega_o^2 + \sqrt{2} \omega_o j \omega)}{-\omega^2} \left[\frac{\epsilon}{d} + \frac{n_d + n_o/A_0}{(M+1)/M} \right] \quad (4-7)$$

The closed loop function $H(\omega)$ is

$$H(\omega) = \frac{\omega_o^2 + \sqrt{2} \omega_o j \omega}{-\omega^2 + \sqrt{2} \omega_o j \omega + \omega_o^2} \quad (4-8)$$

$$\frac{\hat{T}}{d} = H(\omega) \left[\frac{\hat{T}}{d} + \frac{n_d + n_o/A_0}{(M+1)/M} \right] \quad (4-9)$$

The value of $\hat{T}/d$ without noise is

$$\frac{\hat{T}}{d} = H(\omega) \frac{T}{d}$$

$$\frac{\epsilon}{d} = \frac{T - \hat{T}}{d} = \frac{T}{d} (1 - H(\omega)) = \frac{T}{d} \left\{ \frac{-\omega^2}{\omega_o^2 + \sqrt{2} \omega_o j \omega - \omega_o^2} \right\} \quad (4-10)$$

Letting $\frac{T(t)}{d} = at$

$$\frac{T(\omega)}{d} = \frac{a}{-\omega^2}$$

$$\frac{\hat{T}(t)}{d} = at - \frac{\sqrt{2} a}{\omega_o} e^{-\frac{\omega_o}{\sqrt{2}} t} \sin \frac{\omega_o}{\sqrt{2}} t \quad (4-11)$$

$$\frac{\epsilon(t)}{d} = \frac{\sqrt{2} a}{\omega_o} e^{-\frac{\omega_o}{\sqrt{2}} t} \sin \frac{\omega_o}{\sqrt{2}} t \quad (4-12)$$

$$\max \frac{\epsilon(t)}{d} = \frac{a}{2.19 \omega_o} \quad \text{at } t = \frac{\pi}{2\sqrt{2} \omega_o} \quad (4-13)$$

The critical value of ω_o for expected maximum value of a is to be decided from nonlinear analysis. If we limit this as

$$\max. \epsilon/d \leq 1$$

$$\text{then } a/\omega_o \leq 2.19 \quad (4-14)$$

$$E_T^2 = \int_0^\infty \epsilon(t)^2 dt = \frac{d^2 a^2}{2\sqrt{2} \omega_0^3} \quad (4-15)$$

B) Acquisition transient

If we take $D_d(\epsilon)$ only, from the previous equation,

$$\begin{aligned} \frac{\hat{T}}{d} &= \frac{g_0(\omega_0^2 + \sqrt{2}\omega_0 j\omega)}{j\omega\omega_0^2 + g_0(j\omega)^2} D_d(\epsilon) \frac{M}{M+1} \\ &= \frac{1 + \sqrt{2}j\omega/\omega_0}{\frac{\omega_0}{g_0} \frac{j\omega}{\omega_0} + (\frac{j\omega}{\omega_0})^2} D_d(\epsilon) \frac{M}{M+1} \end{aligned} \quad (4-16)$$

Let $x = \epsilon/d$ $y = T/d$ $y-x = \hat{T}/d$ $T = \omega_0 t$ $g_0/\omega_0 = g$

$\frac{j\omega}{\omega_0}$ implies $\frac{1}{\omega_0} \frac{d}{dt} = \frac{d}{dT}$

$D_d(\epsilon) \frac{M}{M+1}$ is denoted $D(x)$

$$D(x) = \begin{cases} 2-x & 1 \leq x \leq 2 \\ x & -1 \leq x \leq 1 \\ -2-x & -2 \leq x \leq -1 \\ 0 & \text{otherwise} \end{cases}$$

$$\frac{dD}{dx} = D'(x) = \begin{cases} 1 & -1 \leq x \leq 1 \\ -1 & -2 \leq x \leq -1 \quad \text{or} \quad 1 \leq x \leq 2 \\ 0 & \text{otherwise} \end{cases}$$

$$\text{then } \left(\frac{1}{g} \frac{d}{dT} + \frac{d^2}{dT^2} \right) (y-x) = \left(1 + \sqrt{2} \frac{d}{dT} \right) D(x) \quad (4-17)$$

$$\ddot{y} + \dot{y}/g = \ddot{x} + \dot{x}/g + D(x) + \sqrt{2} D'(x) \dot{x}$$

$$\text{where } \dot{x} = \frac{dx}{dT} \quad \ddot{x} = \frac{d^2 x}{dT^2} \quad \text{etc.}$$

$$\ddot{x} + \left(\frac{1}{g} + \sqrt{2} D'(x) \right) \dot{x} + D(x) = \ddot{y} + \dot{y}/g \quad (4-18)$$

The slope of phase trajectory γ is

$$\gamma = \frac{\ddot{x}}{\dot{x}} = \frac{d\dot{x}}{dx} = - \frac{D(x) + (\sqrt{2} D'(x) + 1/g) \dot{x} - \ddot{y}/g - \ddot{y}}{\dot{x}} \quad (4-19)$$

If we plot this performance on the phase plane $\dot{x}$ and x , $D'(x)$ and $D(x)$ are the function of only x and we can find the dividing line on $x = -2$, $x = -1$, $x = 1$ and $x = 2$. Let these regions be called A, B, C, D, E as shown in Fig. 4-3.




Fig. 4-3 Regions in Phase Trajectory

Region A and E

$$\left. \begin{aligned} D'(x) = D(x) &= 0 \\ \ddot{x} + \frac{1}{g}\dot{x} &= \ddot{y} + \frac{1}{g}\dot{y} \\ \dot{x} &= \frac{\dot{y}/g + \ddot{y}}{\gamma + 1/g} \end{aligned} \right\} \quad (4-20)$$

γ does not contain x , but is defined only by $\dot{x}$ and the input.

Thus, if $\dot{x} = \dot{y}$ at the initial point, then

$$\begin{aligned} \gamma &= \ddot{y}/\dot{x} \\ \dot{x} &= \frac{\ddot{y} + \frac{1}{g}\dot{y}}{\ddot{y} + \frac{1}{g}\dot{x}} \dot{x} \\ \dot{y} &= \dot{x} \\ x &= y + x_0 \end{aligned} \quad \begin{array}{l} x_0: \text{ initial position} \\ (4-21) \end{array}$$

If $x \neq y$ at $\tau=0$, letting the initial values of x , $\dot{x}$, y , $\dot{y}$ be x_0 , $\dot{x}_0$, 0 , $\dot{y}_0$, and substitute them into the general solution of this equation

$$x = c_1 + c_2 e^{-\gamma/g} + y$$

and we obtain

$$x = y + x_0 + g(\dot{x}_0 - \dot{y}_0)(1 - e^{-\gamma/g}) \quad (4-22)$$

Region B

$$\left. \begin{aligned} D'(x) &= -1 \\ D(x) &= -2 - x \\ \gamma &= - \frac{-2 - x + (\frac{1}{g} - \sqrt{2})\dot{x} - \dot{y}/g - \ddot{y}}{\dot{x}} \\ \dot{x} &= \frac{(2+x) + \dot{y}/g + \ddot{y}}{\gamma + 1/g - \sqrt{2}} \end{aligned} \right\} \quad (4-23)$$

For a constant velocity input, i.e. $\ddot{y} = 0$, the point having a constant $\gamma = k$ draws a line.

$$(k + \frac{1}{g} - 2)\dot{x} - (x + 2 + \dot{y}/g) = 0$$

If g is large enough to approximate $1/g=0$, then upper part of the line combining $(x=-1, \dot{x}=-0.518)$, $(x=-2, \dot{x}=0)$ converges. This line is derived as follows,




Fig. 4-4 Phase Trajectory in Region B

for constant $\gamma=k$

$$(k-\sqrt{2})\dot{x} - (x+2)=0$$

$$\dot{x}\Big|_{x=-1} = -\frac{2+x}{\sqrt{2}-k}\Big|_{x=-1} = -\frac{1}{\sqrt{2}-k} \quad k < 0$$

$$\text{the slope of the line} = k = \frac{\dot{x}_0}{1} = -\frac{1}{\sqrt{2}-k}$$

$$\text{therefore} \quad k^2 - \sqrt{2}k - 1 = 0$$

$$k = -\frac{\sqrt{3}-1}{\sqrt{2}}$$

$$\dot{x}_0 = -\frac{1}{\sqrt{2} + \frac{\sqrt{3}-1}{\sqrt{2}}} = -0.518$$

Region C

$$D(x) = x$$

$$D'(x) = 1$$

$$\gamma = -\frac{x + [\sqrt{2} + 1/g]\dot{x} - \ddot{y}/g - \ddot{y}}{\dot{x}}$$

$$\dot{x} = \frac{-x + \ddot{y}/g + \ddot{y}}{\gamma + 1/g + \sqrt{2}}$$

(4-24)

Region D

$$D(x) = 2-x$$

$$D'(x) = -1$$

$$\gamma = -\frac{2-x + (-\sqrt{2} + 1/g)\dot{x} - \ddot{y}/g - \ddot{y}}{\dot{x}}$$

$$\dot{x} = \frac{-2+x + \ddot{y}/g + \ddot{y}}{\gamma + 1/g - \sqrt{2}}$$

(4-25)

The line which divides the plane into converging and diverging parts is derived by the same way as that in region B.




Fig. 4-5 Phase Trajectory in Region D

The result obtained by CDC 1604 digital computer for $g = \infty$ and several initial conditions is shown in Fig. 4-6, (Computer programming, see Appendix II).

From this figure $\dot{x}=2.35$, $x=0$ at the initial condition is the limit to converge. It implies that $\frac{a}{\omega_0} \leq 2.35$.

Time response of position error and velocity error are shown in Fig. 4-7, 8. From these figures the locking time is approximately $6/\omega_0 \doteq 2\pi/\omega_0$.

The phase trajectory, x vs. τ and $\dot{x}$ vs. τ for $g=10$ are shown in Fig. 4-9, 10, 11. From these figures we can find the position error of 0.2, and the limit of $\dot{y}$ is approximately 2.0. Lock time is also $6/\omega_0 \doteq 2\pi/\omega_0$.

4.2 Noise and its Effect on the tracking

In this section, I would first like to discuss the effect of self-noise; second the effect of the input Gaussian noise, and finally, the effect of the limiter before this stage.

a) Self-noise

Self-noise is a function of time and phase error. Continuing from the last equation (4-2), power spectral density for the time error ϵ being an integer multiple of d is derived as follows;

$$\underline{n_d(t, kd), \text{ where } k=0}$$

The autocorrelation function of this self-noise is the sum of three triangular waves as shown. By the Wiener-Khinchin relation the power

5.2

Fig. 4-6

Phase Trajectory for $k = \infty$




Fig. 4-7

Position error x vs. normalized time τ
for $k = \infty$




Fig. 4-3

Velocity Error $\dot{x}$ vs. Normalized Time τ
for $g=\infty$






Fig. 4-10

Position Error x vs. Normalized Time τ
for $\omega = 10$




$\dot{x}$

Velocity Error $\dot{x}$ vs. Normalized Time τ
For $\omega = 10$



spectral density is the Fourier transform of this wave.

$$\begin{aligned}
 G_{n_s}(\omega, \epsilon=0) &= \frac{1}{M} \left(\frac{\sin \omega d/2}{\omega d/2} \right)^2 \sum_{\substack{n=-\infty \\ n \neq 0}}^{\infty} \delta(\omega - \frac{2\pi n}{Md}) \{ 2 - e^{-j\omega d} - e^{j\omega d} \} \\
 &= 2G_s(\omega)(1 - \cos \omega d)
 \end{aligned} \tag{4-26}$$



$k = \pm 1$

$$G_{n_s}(\omega, \epsilon = \pm d) = G_s(\omega) \tag{4-27}$$

Since $n_s(t, d)$ is the same as signal.

$k = \text{other integer}$

By transforming the autocorrelation function

$$G_{n_s}(\omega, \epsilon = kd) = 2G_s(\omega) [1 - \cos(r-q)\omega d] \tag{4-28}$$

We are interested in the effect of this noise in the linearized region $-d \leq \epsilon \leq d$.

For the extreme case $\epsilon = \pm d$, the power of self-noise in the output of $H(\omega)$ is

$$\begin{aligned}
 \sigma_{n_s}^2 &= \frac{d^2}{2\pi} \int_{-\infty}^{\infty} G_{n_s}(\omega, d) |H(\omega)|^2 d\omega \\
 &= \frac{d^2}{2\pi} \int_{-\infty}^{\infty} \frac{1 + 2(\omega/\omega_0)^2}{1 + (\omega/\omega_0)^4} \frac{1}{M} \left(\frac{\sin \omega d/2}{\omega d/2} \right)^2 \sum_{\substack{n=-\infty \\ n \neq 0}}^{\infty} \delta(\omega - \frac{2\pi n}{Md}) d\omega \\
 &= d^2 \omega_0 d
 \end{aligned} \tag{4-29}$$

For the least extreme case, $\epsilon = 0$

$$\sigma_{n_s}^2 = \frac{4d^2}{M} \sum_{n=-\infty}^{\infty} \frac{1 + 2(\frac{2\pi n}{Md\omega_0})^2}{1 + (\frac{2\pi n}{Md\omega_0})^4} \left(\sin \frac{\pi n}{M} \right)^2 \left(\frac{\sin \frac{\pi n}{M}}{\pi n/M} \right)^2$$

b) The mean-square delay error caused by the input noise

$$\begin{aligned}
 \sigma_{n_s}^2 &= d^2 \left(\frac{M}{M+1} \right)^2 \frac{1}{2\pi} \int_{-\infty}^{\infty} \frac{G_{n_s}(\omega)}{A_0^2} |H(\omega)|^2 d\omega \\
 &= 3.08 d^2 \left(\frac{M}{M+1} \right)^2 \frac{\gamma \omega_0}{A_0^2}
 \end{aligned} \tag{4-30}$$

4.3 The effect of input limiting

By the previous discussion we approximated the input noise as Gaussian with zero mean and the variance σ_n^2 . The signal is a square wave of amplitude $\pm A_0$.

Given a digit which has equal probability of $+A$ or $-A$ with additive Gaussian noise, and if we decide the signal is $\pm A$ according to the polarity of input, the error probability for each digit is derived as follows:

When we defined $A = \sqrt{\frac{1}{2}(1 + e^{-\sigma_n^2/2})} A \sin \theta$, this was derived as an averaged value for some interval, hence if we want to get the probability of error for each digit, we can not use A_0 as the amplitude of the signal.

The probability of error P_E is

$$P_E = P(s(t) = +1)P(\text{output is negative} / s(t) = +1) \\ P(s(t) = -1)P(\text{output is positive} / s(t) = -1) \quad (4-31)$$

The conditional probability of each term is the same value, because additive noise has zero mean and the signal amplitude is the same in absolute value.

$$P_E = 2P(s(t) = +1)P(\text{output is negative} / s(t) = +1) \quad (4-32)$$

The output of the first discriminator is

$$A \cos \theta \sin \theta_0 + A s(t) \sin \theta \cos \theta_0 + n_f(t)$$

θ_0 and n_f are Gaussian, with zero mean and

$$\sigma_{\theta_0}^2 = \frac{3\gamma B_0}{4\sqrt{2} A^2 \cos^2 \theta} + \theta^2 B_0 d$$

$$\sigma_{n_f}^2 = \gamma \frac{2\pi}{d}$$

they are not mutually independent, but the normalized correlation co-efficient ρ is

$$\rho = \frac{B_0 \gamma}{A \cos \theta} / \sigma_{\theta_0} \sigma_{n_f}$$

From eq. (4-32)

$$P(\text{output is negative} / s(t) = +1) \\ = P[A \sin(\theta + \theta_0) + n_f < 0] \\ = P[n_f \leq -A \sin(\theta + \theta_0)] \\ = \frac{1}{2\pi \sigma_{\theta_0} \sigma_{n_f} \sqrt{1-\rho^2}} \int_{-\infty}^{\infty} \int_{-\infty}^{-A \sin(\theta + \theta_0)} \exp \left\{ -\frac{1}{2(1-\rho^2)} \left(\frac{\theta_0^2}{\sigma_{\theta_0}^2} - \frac{2\rho \theta_0 n_f}{\sigma_{\theta_0} \sigma_{n_f}} + \frac{n_f^2}{\sigma_{n_f}^2} \right) \right\} dn_f d\theta_0 \\ \doteq \frac{1}{\sqrt{2\pi} \sigma_{\theta_0}} \int_{-\infty}^{\infty} \exp \left(-\frac{\theta_0^2}{2\sigma_{\theta_0}^2} \right) \operatorname{erf} \left\{ \frac{1}{\sqrt{1-\rho^2}} \left(-\frac{A}{\sigma_{n_f}} \sin(\theta + \theta_0) - \frac{\rho \theta_0}{\sigma_{\theta_0}} \right) \right\} d\theta_0 \quad (4-33)$$

$$\text{where } \operatorname{erf}(x) = \frac{1}{\sqrt{2\pi}} \int_{-\infty}^x e^{-x^2/2} dx$$

Consider a pulse train of m digits, where each digit has probability of error P_E , then if all pulses are 1, the average of this pulse train is derived as follows.

The number of error k in m digits distributes binormally, and if m is large enough and mP_E is not small, then this distribution can be approximated by a normal distribution with mean $= mP_E$, variance $mP_E(1-P_E)$. In this case each error causes the decrease of $2/m$ in the average, and this decrease is normally distributed.

The decrease of the averaged voltage v is, thus

$$p(v) = \frac{1}{\sqrt{2\pi} \sqrt{\frac{4P_E(1-P_E)}{m}}} e^{-\frac{(v-2P_E)^2}{2 \left(\frac{4P_E(1-P_E)}{m} \right)}} \quad (4-34)$$

If the pulse train is composed with the same number of +1 and -1, i.e. $m/2$ of positive pulses and $m/2$ of negative pulses, then an error which occurred in positive pulses causes negative error $2/m$ in the average voltage and the same for an error in negative pulses.

x : positive error voltage caused by errors in negative pulses

y : negative error voltage caused by errors in positive pulses

Since the error for each digit is independent, x and y are independent because they are the error caused by only negative or positive pulses.

$$p(x) = \frac{1}{\sqrt{2\pi} \sqrt{\frac{2P_E(1-P_E)}{m}}} \exp \left\{ -\frac{(x-P_E)^2}{2 \left(\frac{2P_E(1-P_E)}{m} \right)} \right\}$$

$$p(y) = \frac{1}{\sqrt{2\pi} \sqrt{\frac{2P_E(1-P_E)}{m}}} \exp \left\{ -\frac{(y+P_E)^2}{2 \left(\frac{2P_E(1-P_E)}{m} \right)} \right\}$$

Since they are independent, the probability distribution of $u=(x+y)$ is

$$\begin{aligned} p(u) &= \int_{-\infty}^{\infty} p_x(x) p_y(u-x) dx \\ &= \frac{1}{2\pi \left(\frac{2P_E(1-P_E)}{m} \right)} \int_{-\infty}^{\infty} \exp \left\{ -\frac{1}{2 \left(\frac{2P_E(1-P_E)}{m} \right)} ((x-P_E)^2 + (u+P_E-x)^2) \right\} dx \\ &= \frac{1}{2\pi \sigma^2} \int_{-\infty}^{\infty} \exp \left\{ -\frac{1}{2\sigma^2} (z^2 + (u-z)^2) \right\} dz \quad \text{where } x-P_E = z \quad \frac{2P_E(1-P_E)}{m} = \sigma^2 \\ &= \frac{1}{\sqrt{2\pi} \sqrt{2\sigma^2}} \exp \left\{ -\frac{u^2}{2(2\sigma^2)} \right\} \\ &= \frac{1}{\sqrt{2\pi} \sqrt{\frac{4P_E(1-P_E)}{m}}} \exp \left\{ -\frac{u^2}{2 \left(\frac{4P_E(1-P_E)}{m} \right)} \right\} \quad (4-35) \end{aligned}$$

This variance is equal to that in the positive pulse train.

The effects these digit errors cause in the next binary discriminator, will be discussed in two phases, first at the locked point, and this can be considered as a phase jitter in the phase-locked position, and second at the limit where the phase error becomes $\pm d$. This may be considered as the modification of $D_d(\epsilon)$ curve. These two effects will show the analysis of the system.

When one digit error occurs in the input, how does this appear in the outputs of two crosscorrelators? If the system is locked in phase, $\epsilon = 0$, the outputs are also a cyclic permutation of that m-sequence and their phases differ by 1 digit. Since the autocorrelation function of this sequence is nearly zero for $\epsilon = \pm d$, the errors introduced in the outputs of the crosscorrelators do not have any relation to their polarity except the fact that they occurred at the same time. About the polarity, from the characteristics of the randomness of m-sequence, the probability that both errors are positive or negative is $\frac{1}{4}$ each, and the probability the sum is zero is $\frac{1}{2}$. This implies the error probability is decreased by a factor of 2, and we can use $P_E/2$ instead of P_E , and the change in the average voltage output caused by one error becomes double.

Thus, we can modify the equation of the noise voltage as follows.

$$p(u) = \frac{1}{\sqrt{2\pi} \sqrt{\frac{16(P_E/2)(1-P_E/2)}{m}}} \exp \left\{ -\frac{u^2}{2 \left(\frac{16(P_E/2)(1-P_E/2)}{m} \right)} \right\} \quad (4-36)$$

For the case of $\epsilon = d$, one error always appears as negative, and another as positive of negative. This time we do not need to modify P_E , but we can add two effects.

$$p(u) = \frac{1}{\sqrt{2\pi} \sqrt{\frac{8P_E(1-P_E)}{m}}} \exp \left\{ -\frac{(u-2P_E)^2}{2 \left(\frac{8P_E(1-P_E)}{m} \right)} \right\}$$

We have been discussing the effect of noise on the average through m digits so far, and now we have to make sure of the meaning of the average.

The inverse Fourier transform of $H(\omega)$, $h(t)$ is

$$h(t) = \sqrt{2} \omega_0 e^{-\frac{\omega_0}{\sqrt{2}} t} \cos \frac{\omega_0}{\sqrt{2}} t$$

The response of this filter to a pulse of height 1 and duration d is,

if we take the response after time d ,

$$\frac{\omega_0 d}{\sqrt{2}} e^{-\frac{\omega_0}{\sqrt{2}} t} \sqrt{2} \sin\left(\frac{\omega_0}{\sqrt{2}} t + \frac{\pi}{4}\right)$$

Since the chance of error is very small, it will be improbable that the digit in error will be discovered. Therefore we can neglect the response of this filter in the digit duration and assume this as an impulse response.

When we look backward for a time interval of T , standing at an arbitrary time t_1 , if we use a real averaging device, the value at t_1 is, assuming there are k impulses to occur in T ,

$$u_1 = \frac{1}{T} \int_{t_1-T}^{t_1} \sum_{i=1}^k d \delta(t-t_i) dt = \frac{k d}{T}.$$

If we use $H(\omega)$ as an averager, the output average differs depending upon the positions of impulses, but when we think of the interval of each impulse, this is approximately distributed exponentially, and after taking many intervals T containing k impulses, we find k impulses are distributed in equal intervals as an average.

Thus, the output average is the integration of that response. The time interval T should be determined for $H(\omega)$, and looking at the response

$$\frac{\omega_0 d}{\sqrt{2}} e^{-\frac{\omega_0}{\sqrt{2}} t} \sqrt{2} \sin\left(\frac{\omega_0}{\sqrt{2}} t + \frac{\pi}{4}\right), \text{ we can neglect the effect of the tail after } t = \frac{3\pi\sqrt{2}}{4\omega_0}.$$

$$T = \frac{3\pi}{4} \frac{\sqrt{2}}{\omega_0} \quad (4-37)$$

$$\begin{aligned} u_2 &= \frac{k d}{T} \int_0^T \frac{\omega_0}{\sqrt{2}} e^{-\frac{\omega_0}{\sqrt{2}} t} \sqrt{2} \sin\left(\frac{\omega_0}{\sqrt{2}} t + \frac{\pi}{4}\right) dt \\ &= \frac{k d 4 \omega_0^2}{3\pi \sqrt{2} \sqrt{2}} \int_0^{\frac{3\pi\sqrt{2}}{4\omega_0}} \left[e^{-\frac{\omega_0}{\sqrt{2}} t} \left(\sin \frac{\omega_0}{\sqrt{2}} t + \cos \frac{\omega_0}{\sqrt{2}} t \right) \right] dt \\ &= \frac{4 k \omega_0 d}{3\pi \sqrt{2}} = \frac{k d}{\frac{3\sqrt{2}}{4} \frac{\pi}{\omega_0}} = \frac{k d}{T} \end{aligned} \quad (4-38)$$

$$m = \frac{3\pi\sqrt{2}}{4} \frac{1}{\omega_0} / d \quad (4-39)$$

Thus we can approximate the effect of $H(\omega)$ by the effect of averaging.

CHAPTER V

THRESHOLD FOR THIS SYSTEM

5.1 Summary of the System Performance

When we evaluate the performance of a phase lock system, maximum frequency deviation, or in other words, maximum target velocity that a tracking system can acquire, and transient time for phase lock, probability of cycles slipping and r.m.s. phase error at the steady state will be considered. The problem of the cycles slipping is considered very important for this system, because the acquisition time in A, E region in Fig. 4-3 can be very large. We can not allow cycle slip in the delay lock discriminator. Cycle slip is related to r.m.s. phase error at the steady state. From the experimental results of W. F. Roland, [7] we can find the linearity of $\sigma_{\theta_0}^2$ vs. B_0 up to 20-30 degree, and the expected number of cycle slip per $\frac{2\pi}{B_0}$ is

$6 \cdot 10^{-4}$	for	$\sigma_{\theta_0} : 20^\circ$
$6 \cdot 10^{-3}$	for	$\sigma_{\theta_0} : 25^\circ$
$2.35 \cdot 10^{-2}$	for	$\sigma_{\theta_0} : 30^\circ$

If we use equation (3-3), the time for $e^{-\frac{B_0}{\sqrt{2}}t} = 0.1$ is $\frac{2.32\sqrt{2}}{B_0} \approx \frac{\pi}{B_0}$.

This is for the initial position error of zero, and we can approximately use twice the value of it, $\frac{2\pi}{B_0}$, as an acquisition time from the initial error of π .

Let the expected number of cycles slip per $\frac{2\pi}{B_0}$ be p_s and the settling time be $\frac{2\pi}{B_0}$, then as an average

$$l_s = p_s \frac{B_0}{2\pi} dM \quad (5-1)$$

is the number of cycles slip in one period. If one cycle of slip occurs, $\frac{2\pi}{B_0}$ in Md is in transient response and it can cause longer transient

Carrier frequency	200 Megacycles
Pulse duration, d	5 Microsecond (2500 feet)
Number of digits in one period	$M \approx 1200$
	$T = Md = 5$ Milisecond
Maximum target velocity, v	3 Mach, 3000 feet/sec
Input S/N ratio	less than 0 dB

a) Lower limit of B_o ,

$$\Delta\omega|_{\max} = \frac{2v}{c} \omega_c = \frac{6000}{10^9} \cdot 2\pi \cdot 200 \times 10^6 \approx 7550 \approx 8000 \text{ rad/sec}$$

$$B_o \geq \frac{\Delta\omega}{2} \approx 4000 \text{ rad/sec}$$

for this B_o , $t_{\text{lock}} \approx \frac{2\pi}{B_o} \approx 1.6 \text{ msec}$

This will be short enough comparing with a period of $Md = 5 \text{ msec}$ for the first acquisition and we do not need to increase B_o .

For the delay lock discriminator we put

$$T(t) =adt \quad \text{in eq. (4-11).}$$

$$\frac{dT}{dt} = \frac{2v}{c} = ad$$

$$a = \frac{2v}{c} \frac{1}{d} \approx 1.2$$

$$\frac{A}{\omega_o} \leq 2.0$$

$$\omega_o \geq 0.6 \text{ rad/sec}$$

$$\text{but } t_{\text{lock}} \approx \frac{2\pi}{\omega_o} \quad (5-5)$$

$$\text{for } \omega_o = 0.6 \quad t_{\text{lock}} = 10 \text{ sec}$$

This is too large for this operation, and we need to make ω_o large in the limit where the cycle slip does not occur.

b) The number of cycle slips per $\frac{2\pi}{B_o}$

$$l_s = p_s \frac{B_o}{2\pi} Md \quad (5-6)$$

$$B_o = 4000 \quad d = 5 \cdot 10^{-6} \quad M = 1200$$

$$l_s = 4p_s$$

Once a cycle slip occurs, it takes 1.6 msec to recover and this

becomes a loss of about one third of a period. Thus we want to limit 1_d in $3 \cdot 10^{-2}$, or r.m.s. phase error up to 25° .

c) $\sigma_{\theta_0}^2 = \sigma_{\theta_n}^2 + \sigma_{\theta_s}^2$

$$\sigma_{\theta_n}^2 = \frac{\gamma}{2A^2 \cos^2 \theta} \cdot 1.06 B_0 = \frac{1}{2 \cos^2 \theta} \frac{1}{K} \left(\frac{1.06 B_0}{2\pi \times 400 \times 10^3} \right)$$

where K is input S/N ratio

$$\sigma_{\theta_s}^2 = B_0 d \theta^2$$

$\sigma_{\theta_n}^2, \sigma_{\theta_s}^2$ and $\sigma_{\theta_0}^2$ vs. θ for various values of K are shown in Fig. 5-1.

d) $\frac{A_0^2}{A^2} = \frac{1}{2} (1 + e^{-\sigma_{\theta_0}^2/2}) \sin^2 \theta$

Under the limitation of $\sigma_{\theta_0}^2 \leq 0.19$ ($= (25^\circ)^2$), we can plot $\frac{A_0^2}{A^2}$ vs. θ for various K, as shown in Fig. 5-2.

From Fig. 5-2, we can find θ which maximizes $\frac{A_0^2}{A^2}$ with respect to K, and this is in Fig. 5-3. The maximized $\frac{A_0^2}{A^2}$ vs. K is shown in Fig. 5-4.


e) The mean square delay error σ_n^2 is the sum of the contribution of noise and self-noise. Taking the worst value of self-noise, from eq. (4-30) and (4-29),

$$\frac{\sigma_n^2}{d^2} \doteq 3.08 \frac{\omega_0}{K (A_0^2/A^2) (2 \cdot 200 \cdot 10^3)} + \omega_0 d \quad (5-7)$$

In Fig. 5-5, we showed $\frac{\sigma_n^2}{d^2}$ vs. K with maximum value of $\frac{A_0^2}{A^2}$, for various values of ω_0 . In order to avoid cycle slip, we limited $\sigma_n/d \leq 0.2$, and the maximum value of ω_0 vs K to satisfy this limitation, and t_{lock} vs. K for this ω_0 are finally shown in Fig. 5-6.

From these figures, we can see that this system can not show good performance for the S/N ratio less than -15 dB.

5.3 The effect of a limiter before the delay lock discriminator does not improve S/N ratio, because for low S/N ratio, P_e approaches to $\frac{1}{2}$ and phase lock control voltage $D_d(\epsilon)$ effectively decreases to zero.



$$\frac{A_0^2}{A^2}$$




Fig 5-2 A_0^2/A^2 vs. θ for various K

Fig. 5-3 Optimum θ vs. K






Fig. 5-4 Maximum P/A^2 vs. K








Fig. 5-6 ω_0 and Acquisition Time t_{lock} vs. K

CHAPTER VI

CONCLUSION

The result in Chapter 5 shows that if we use the demodulator in the limit to avoid cycle slip, the amplitude of the output signal A_o is mainly decided by $\sin \theta$, and r.m.s. phase error σ_θ is also determined mainly by the noise input near the upper limit of $25\sim 30^\circ$. Eq. (5-7) shows that the variance of delay error σ_n^2 is the sum of input noise and self-noise and both are proportional to ω_b , therefore for better S/N ratio the self-noise is dominant. We are interested more in the low S/N ratio region than in the high one, and we can also approximate σ_n^2 by the contribution of the input noise.

When we want to design this phase lock system, we will find several opposing factors.

- 1) The phase lock ability over the range of the frequency deviation limits the lower side of B_o , ω_o .
- 2) The cycle slip bounds the upper limit of θ and B_o , ω_o with respect to K .
- 3) For a satisfactory acquisition time, we have to get large B_o and ω_o .
- 4) The effect of d is related to the input bandwidth and ω_o . d is also related to the range resolution of a radar. Small d will offer a good resolution, but on the other hand it costs S/N ratio and limits the input frequency deviation.

We tried to solve the problem for a constant S/N ratio in Chapter 5. Actually input S/N ratio can not be constant in a system application, and we can estimate only the least desirable value or a range of S/N ratio. When we use this system for ranging, σ_n^2 does not have much meaning in itself, but is very important as a cause of cycle slip. Looking through

these four factors, 2 and 3 are especially significant in opposing each other, and we will finally decide B_0 , and ω_0 by applying a weighting factor. The actual designing process must be decided according to each case, and we want to point out the fundamental relations between the above four factors, for they must be further investigated.

CHAPTER VII

ACKNOWLEDGEMENT

I appreciate the assistance of Professor C. F. Klammer, Jr., for his suggestions and advice about PN sequences, and the idea for this system as a whole.

BIBLIOGRAPHY

1. Barker, R. H. "Group Synchronizing of Binary Digital Systems", in Communication Theory, Jackson, W. ed., New York, Academic Press, 1953.
2. Baumert, L. D. "Codes with Special Correlation", in Digital Communication, Golomb, S. W., ed., Prentice-Hall, 1964.
3. Easterling, M. F. "Applications to Ranging", in Digital Communication, Golomb, S. W., ed., Prentice-Hall, 1964.
4. Golomb, S. W. "Introduction to Digital Communication", in Digital Communication, Golomb, S. W., ed., Prentice-Hall, 1964.
5. Jaffe, R. and Rechtin, E. Design and Performance of Phase-Lock Circuits Capable of Near-Optimum Performance over a Wide Range of Input Signal and Noise Levels. Institute of Radio Engineers, Transaction on Information Theory. v. IT-1, March 1955.
6. Jauregui, Jr. S. A Theoretical Study of Complementary Binary Code Sequences and A Computer Search for New Kernels. Ph.D. Dissertation, U.S. Naval Postgraduate School, May 1962.
7. Roland, W. F. A Threshold Criterion for Phase Locked Design. Thesis for Master of Science, U.S. Naval Postgraduate School, May, 1963.
8. Spilker, J. J. Delay-Lock Tracking of Binary Signals. Institute of Electrical and Electronics Engineers, Transactions on Space Electronics and Telemetry. v. SET-9, March 1963.
9. Springett, J. C. Telemetry and Command Techniques for Planetary Spacecraft. Technical Report 32-495, Jet Propulsion Laboratory, January, 1965.
10. Viterbi, A. J. "Phase-Lock-Loop Systems", in Space-Communications, Balakrishnan, A. V., ed., McGraw-Hill, 1963.

APPENDIX I

SELF-NOISE

The phase error output by signal $s(t)$ itself is $\theta S(\omega)H(\omega)$ considering the relation shown in Fig. 3-5.

$$\begin{aligned}\sigma_{\theta_s}^2 &= \frac{1}{2\pi} \int_{-\infty}^{\infty} \theta^2 G_s(\omega) |H(\omega)|^2 d\omega \\ &= \frac{\theta^2}{2\pi} \int_{-\infty}^{\infty} \frac{1 + 2(\omega/B_0)^2}{1 + (\omega/B_0)^4} \frac{1}{M} \left(\frac{\sin \omega d'/2}{\omega d'/2} \right)^2 \sum_{\substack{n=-\infty \\ n \neq 0}}^{\infty} \delta(\omega - \frac{2\pi n}{Md'}) d\omega \\ &= \theta^2 \frac{1}{M} \sum_{\substack{n=-\infty \\ n \neq 0}}^{\infty} \frac{1 + 2(2\pi n/Md'B_0)^2}{1 + (2\pi n/Md'B_0)^4} \left(\frac{\sin \frac{2\pi n}{B_0 d'} \frac{d'}{2}}{\frac{2\pi n}{B_0 d'} \frac{d'}{2}} \right)^2 \\ &= \theta^2 \frac{1}{M} \frac{Md'}{2\pi} \sum_{\substack{n=-\infty \\ n \neq 0}}^{\infty} \frac{1 + 2(2\pi n/Md'B_0)^2}{1 + (2\pi n/Md'B_0)^4} \left(\frac{\sin \frac{2\pi n}{B_0 d'} \frac{d'}{2}}{\frac{2\pi n}{B_0 d'} \frac{d'}{2}} \right)^2 \frac{2\pi}{Md'}\end{aligned}$$

Since M is very large, $\frac{2\pi}{Md'}$ is very small and we can approximate this relation by an integral form.


$$\begin{aligned}\sigma_{\theta_s}^2 &\doteq \theta^2 d' \frac{1}{2\pi} \int_{-\infty}^{\infty} \frac{1 + 2(\omega/B_0)^2}{1 + (\omega/B_0)^4} \left(\frac{\sin \omega d'/2}{\omega d'/2} \right)^2 d\omega \quad z = \omega/B_0 \\ &= \theta^2 B_0 d' \frac{1}{2\pi} \int_{-\infty}^{\infty} \frac{z^2 + 1/2}{z^4 + 1} \left(\frac{\sin B_0 d' z/2}{B_0 d' z/2} \right)^2 dz\end{aligned}$$

$$\begin{aligned}\text{Let } I &= \frac{2B_0 d'}{2\pi} \int_{-\infty}^{\infty} \frac{z^2 + 1/2}{z^4 + 1} \left(\frac{\sin B_0 d' z/2}{B_0 d' z/2} \right)^2 dz \\ I &= \frac{2B_0 d'}{2\pi} \int_{-\infty}^{\infty} \frac{(z + j\frac{1}{\sqrt{2}})(z - j\frac{1}{\sqrt{2}}) \frac{1}{z} (1 - \frac{1}{z} e^{jB_0 d' z} - \frac{1}{z} e^{-jB_0 d' z})}{(z - \frac{1}{\sqrt{2}}(1+j))(z - \frac{1}{\sqrt{2}}(-1+j))(z - \frac{1}{\sqrt{2}}(1-j))(z - \frac{1}{\sqrt{2}}(-1-j)) (\frac{B_0 d'}{2})^2 z^2} dz \\ I_1 &= \frac{2B_0 d'}{2\pi} \frac{1}{2} \int_{-\infty}^{\infty} \frac{z^2 + 1/2}{(z^4 + 1)(B_0 d'/2)^2 z^2} dz \\ I_2 &= \frac{2B_0 d'}{2\pi} \frac{1}{4} \int_{-\infty}^{\infty} \frac{(z^2 + 1/2) e^{jB_0 d' z}}{(z^4 + 1)(B_0 d'/2)^2 z^2} dz \\ I_3 &= \frac{2B_0 d'}{2\pi} \frac{1}{4} \int_{-\infty}^{\infty} \frac{(z^2 + 1/2) e^{-jB_0 d' z}}{(z^4 + 1)(B_0 d'/2)^2 z^2} dz \\ I &= I_1 - I_2 - I_3\end{aligned}$$

$$\text{Moreover, let } g(z) = \frac{2B_0 d'}{2\pi} \frac{1}{z} \frac{z^2 + 1/2}{(z^4 + 1)(B_0 d'/2)^2 z^2}$$

and consider contour integrals along the paths a , r , Γ_1 or Γ_2 .

Since $B_0 d'$ is positive, the contributions of the integral path Γ_1 to the contour integrals $\int_C g(z) dz$, and $\frac{1}{2} \int_C g(z) e^{jB_0 d' z} dz$, and Γ_2 to $\frac{1}{2} \int_C g(z) e^{-jB_0 d' z} dz$



are all zero. The integral along the path Γ does not converge to zero for each integral as $r \rightarrow 0$, but the sum

$$\int_{\Gamma} g(z) dz = \int_{\Gamma} \frac{1}{z} g(z) e^{jB_0 d' z} dz - \int_{\Gamma} \frac{1}{z} g(z) e^{-jB_0 d' z} dz$$

converges as follows.

$$\begin{aligned} & \lim_{r \rightarrow 0} \left\{ \int_{\Gamma} g(z) dz - \frac{1}{2} \int_{\Gamma} g(z) e^{jB_0 d' z} dz - \frac{1}{2} \int_{\Gamma} g(z) e^{-jB_0 d' z} dz \right\} \\ &= \lim_{r \rightarrow 0} \left\{ \frac{1}{2} \frac{2B_0 d'}{2\pi} \left[\int_{\pi}^0 \frac{\frac{1}{2} r j e^{j\theta}}{(B_0 d'/2)^2 r^2 e^{j2\theta}} d\theta - \frac{1}{2} \int_{\pi}^0 \frac{\frac{1}{2} r j e^{j\theta}}{(B_0 d'/2)^2 r^2 e^{j2\theta}} d\theta - \frac{1}{2} \int_{\pi}^0 \frac{\frac{1}{2} r j e^{j\theta}}{(B_0 d'/2)^2 r^2 e^{j2\theta}} d\theta \right] \right\} \\ &= \lim_{r \rightarrow 0} \left\{ \frac{1}{2} \frac{2B_0 d'}{2\pi} \int_{\pi}^0 \frac{\frac{1}{2} j (1-1)}{(B_0 d'/2)^2 r e^{j\theta}} d\theta \right\} \\ &= 0 \end{aligned}$$

Therefore $I = I_1 - I_2 - I_3$

$$\begin{aligned} &= 2\pi j \left\{ \sum_{\text{UHP}} (\text{residue for } g(z)) - \frac{1}{2} \sum_{\text{UHP}} (\text{residue for } g(z) e^{jB_0 d' z}) \right. \\ &\quad \left. + \frac{1}{2} \sum_{\text{LHP}} (\text{residue for } g(z) e^{-jB_0 d' z}, \text{ including } z=0) \right\} \end{aligned}$$

For I_1 , the sum of residues is $\frac{\sqrt{2}}{2B_0 d'}$

$$I_2, \quad \frac{\sqrt{2}}{4B_0 d'} e^{-\frac{B_0 d'}{\sqrt{2}}} \left\{ 3 \sin \frac{B_0 d'}{\sqrt{2}} + \cos \frac{B_0 d'}{\sqrt{2}} \right\}$$

residue of $z=0$ is $-j \frac{1}{2\pi}$

$$I_3, \quad -1 + \frac{\sqrt{2}}{4B_0 d'} e^{-\frac{B_0 d'}{\sqrt{2}}} \left\{ 3 \sin \frac{B_0 d'}{\sqrt{2}} + \cos \frac{B_0 d'}{\sqrt{2}} \right\}$$

$$\begin{aligned} I &= \frac{\sqrt{2}}{2B_0 d'} - \frac{\sqrt{2}}{4B_0 d'} e^{-\frac{B_0 d'}{\sqrt{2}}} \left\{ 3 \sin \frac{B_0 d'}{\sqrt{2}} + \cos \frac{B_0 d'}{\sqrt{2}} \right\} + 1 - \frac{\sqrt{2}}{4B_0 d'} \left\{ 3 \sin \frac{B_0 d'}{\sqrt{2}} + \cos \frac{B_0 d'}{\sqrt{2}} \right\} \\ &= 1 + \frac{\sqrt{2}}{2B_0 d'} \left(1 - 3 e^{-\frac{B_0 d'}{\sqrt{2}}} \sin \frac{B_0 d'}{\sqrt{2}} - e^{-\frac{B_0 d'}{\sqrt{2}}} \cos \frac{B_0 d'}{\sqrt{2}} \right) \end{aligned}$$

If $B_0 d$ is small enough to neglect second power,

$$I = 1 + \frac{\sqrt{2}}{2B_0 d} \left\{ 1 - 3 \left(1 - \frac{B_0 d}{\sqrt{2}} \right) \frac{B_0 d}{\sqrt{2}} - \left(1 - \frac{B_0 d}{\sqrt{2}} \right) \right\}$$

$$= \frac{3\sqrt{2}}{4} B_0 d = 1.06 B_0 d$$

Thus $\sigma_{\theta_s}^2 \doteq \theta^2 B_0 d$

APPENDIX II

COMPUTER PROGRAM FOR EQUATION (4-18)

```
PROGRAM ACQUIRE
DIMENSION X(30),XDOT(30),C(15)
C(10)=1.
1  CALL INTEG1(T,X,XDOT,C)
   IF (X(1)+2.0) 10,11,12
12  IF (X(1)+1.0) 11,13,14
14  IF (X(1)-1.0) 13,13,15
15  IF (X(1)-2.0) 16,16,10
10  DX=0.0
   DXDOT=0.0
   GO TO 2
11  DX=-2.0-X(1)
   GO TO 3
16  DX=2.0-X(1)
3   DXDOT=-1.0
   GO TO 2
13  DX=X(1)
   DXDOT=1.0
2   ACCE=C(1)
   SPED=C(1)*T+C(2)
   ERROR=C(3)*SPED+ACCE-(C(3)+1.414213*DXDOT)*X(2)-DX
   XDOT(1)=X(2)
   XDOT(2)=ERROR
   GO TO 1
END
```

END

For $g=\text{infinity}$

time; from 0. to 9.0, with interval 0.005

$C(1)=0.$

$C(2)=y$

$C(3)=1/g=0.$

Initial value of $X(1)=-2.0$

$X(2)=\dot{y}$

For $g=10$

time; from 0. to 14.0, with interval 0.01

$C(1)=0$

$C(2)=y$

$C(3)=1/g=0.1$

Initial value of $X(1)=-2.0$

$X(2)=\dot{y}$

APPENDIX III
SUBROUTINE INTEG 1

This subroutine provides a simple but moderately flexible means for the solution of ordinary differential equations, employing integration by the fourth-order Runge-Kutta numerical method. Input, and both print and graph output routines are built in. The step size of integration can be changed by appropriate data input and/or programming.

Title: Runge-Kutta Solution of Ordinary Differential Equations
with Built-in Input and Output Routines

CO-OP ID: D2-NPS-INTEG1 (FORTRAN 60)

Programmer: J. R. Ward

Date: June 1964

INITIAL DISTRIBUTION LIST

	No. Copies
1. Defense Documentation Center Cameron Station Alexandria, Virginia 22314	20
2. Library U.S. Naval Postgraduate School, Monterey, California	2
3. Chief of Maritime Staff Maritime Staff Office Akasakahinoki-cho, Minato-ku, Tokyo, Japan	2
4. Prof. C. F. Klammer, Jr. (Thesis Advisor) Department of Electrical Engineering U.S. Naval Postgraduate School, Monterey, California	1
5. LCDR. Yukio Zaima, JMSDF Electronics Engineering Curriculum U.S. Naval Postgraduate School, Monterey, California	2
6. LCDR. Abolfath Ardalan Electronics Engineering Curriculum U.S. Naval Postgraduate School, Monterey, California	1

DOCUMENT CONTROL DATA - R&D

(Security classification of title, body of abstract and indexing annotation must be entered when the overall report is classified)

1. ORIGINATING ACTIVITY (Corporate author)

U. S. NAVAL POSTGRADUATE SCHOOL
MONTEREY, CALIFORNIA

2a. REPORT SECURITY CLASSIFICATION

UNCLASSIFIED

2b. GROUP

N/A

3. REPORT TITLE

A PHASE LOCK SYSTEM FOR A SIGNAL MODULATED BY A PN SEQUENCE

4. DESCRIPTIVE NOTES (Type of report and inclusive dates)

THESIS FOR MASTER OF SCIENCE IN ELECTRONICS ENGINEERING

5. AUTHOR(S) (Last name, first name, initial)

ZAIMA YUKIO
LIEUTENANT COMMANDER, JAPANESE MARITIME SELF-DEFENCE FORCE

6. REPORT DATE

MAY 1966

7a. TOTAL NO. OF PAGES

62

7b. NO. OF REFS

10

8a. CONTRACT OR GRANT NO.

N/A

b. PROJECT NO.

9a. ORIGINATOR'S REPORT NUMBER(S)

N/A

9b. OTHER REPORT NO(S) (Any other numbers that may be assigned this report)

N/A

10. AVAILABILITY/LIMITATION NOTICES

(1) "Qualified requesters may obtain copies of this report from DDC."

11. SUPPLEMENTARY NOTES

N/A

12. SPONSORING MILITARY ACTIVITY

U.S. NAVAL POSTGRADUATE SCHOOL
MONTEREY,

13. ABSTRACT

The dynamics of phase locked loops have been studied by many investigators for the cases of either a pure sinusoidal signal or for pseudo noise (PN) sequence. This dissertation presents an analysis of a phase locked system consisting of sinusoidal carrier modulated with a PN sequence. The effect of the modulation index of the phase shift modulation and the design of a loop filter for coherent detection of a PN sequence are analysed. Additionally, the error probability for each digit, when a likelihood detector is used in front of the delay lock discriminator for a PN sequence, is also converted to the delay error of the phase lock loop.

14.

KEY WORDS

Maximum-length linear shift register sequence

Phase locked loop

Delay locked discriminator

Band limited white Gaussian noise

Phase tracking and acquisition performance

Effects of noise on the phase tracking

LINK A

LINK B

LINK C

ROLE

WT

ROLE

WT

ROLE

WT

INSTRUCTIONS

1. **ORIGINATING ACTIVITY:** Enter the name and address of the contractor, subcontractor, grantee, Department of Defense activity or other organization (*corporate author*) issuing the report.

2a. **REPORT SECURITY CLASSIFICATION:** Enter the overall security classification of the report. Indicate whether "Restricted Data" is included. Marking is to be in accordance with appropriate security regulations.

2b. **GROUP:** Automatic downgrading is specified in DoD Directive 5200.10 and Armed Forces Industrial Manual. Enter the group number. Also, when applicable, show that optional markings have been used for Group 3 and Group 4 as authorized.

3. **REPORT TITLE:** Enter the complete report title in all capital letters. Titles in all cases should be unclassified. If a meaningful title cannot be selected without classification, show title classification in all capitals in parenthesis immediately following the title.

4. **DESCRIPTIVE NOTES:** If appropriate, enter the type of report, e.g., interim, progress, summary, annual, or final. Give the inclusive dates when a specific reporting period is covered.

5. **AUTHOR(S):** Enter the name(s) of author(s) as shown on or in the report. Enter last name, first name, middle initial. If military, show rank and branch of service. The name of the principal author is an absolute minimum requirement.

6. **REPORT DATE:** Enter the date of the report as day, month, year; or month, year. If more than one date appears on the report, use date of publication.

7a. **TOTAL NUMBER OF PAGES:** The total page count should follow normal pagination procedures, i.e., enter the number of pages containing information.

7b. **NUMBER OF REFERENCES:** Enter the total number of references cited in the report.

8a. **CONTRACT OR GRANT NUMBER:** If appropriate, enter the applicable number of the contract or grant under which the report was written.

8b, 8c, & 8d. **PROJECT NUMBER:** Enter the appropriate military department identification, such as project number, subproject number, system numbers, task number, etc.

9a. **ORIGINATOR'S REPORT NUMBER(S):** Enter the official report number by which the document will be identified and controlled by the originating activity. This number must be unique to this report.

9b. **OTHER REPORT NUMBER(S):** If the report has been assigned any other report numbers (*either by the originator or by the sponsor*), also enter this number(s).

10. **AVAILABILITY/LIMITATION NOTICES:** Enter any limitations on further dissemination of the report, other than those

imposed by security classification, using standard statements such as:

- (1) "Qualified requesters may obtain copies of this report from DDC."
- (2) "Foreign announcement and dissemination of this report by DDC is not authorized."
- (3) "U. S. Government agencies may obtain copies of this report directly from DDC. Other qualified DDC users shall request through _____."
- (4) "U. S. military agencies may obtain copies of this report directly from DDC. Other qualified users shall request through _____."
- (5) "All distribution of this report is controlled. Qualified DDC users shall request through _____."

If the report has been furnished to the Office of Technical Services, Department of Commerce, for sale to the public, indicate this fact and enter the price, if known.

11. **SUPPLEMENTARY NOTES:** Use for additional explanatory notes.

12. **SPONSORING MILITARY ACTIVITY:** Enter the name of the departmental project office or laboratory sponsoring (*paying for*) the research and development. Include address.

13. **ABSTRACT:** Enter an abstract giving a brief and factual summary of the document indicative of the report, even though it may also appear elsewhere in the body of the technical report. If additional space is required, a continuation sheet shall be attached.


It is highly desirable that the abstract of classified reports be unclassified. Each paragraph of the abstract shall end with an indication of the military security classification of the information in the paragraph, represented as (TS), (S), (C), or (U).

There is no limitation on the length of the abstract. However, the suggested length is from 150 to 225 words.

14. **KEY WORDS:** Key words are technically meaningful terms or short phrases that characterize a report and may be used as index entries for cataloging the report. Key words must be selected so that no security classification is required. Identifiers, such as equipment model designation, trade name, military project code name, geographic location, may be used as key words but will be followed by an indication of technical context. The assignment of links, roles, and weights is optional.

thesZ23

A phase lock system for a signal modulat



3 2768 001 90403 0

DUDLEY KNOX LIBRARY